



# HDBT to HDMI Receiver - True1

xVision Converter Series



#XVVHDBT2HDMIT1

Professional equipment in mission-critical applications is all about reliability and confidence. So we started with a clean sheet, and built what might soon become your most trustworthy piece of equipment. Introducing the world's first video converters truly designed for the road. Video converters nowadays are used everywhere on professional A/V events, presentations, live shows and tours and often have a critical role. Yet, they are often the weakest link in the signal chain. Low quality connectors, weak enclosure, external consumer-grade power supply, and overall barebones design that all contribute to a generally unreliable piece of equipment. We wanted to change that, so we designed the xVision Video Converters.

## Connections

### Video Input

HDBaseT 1.0 on shielded EtherCON connector

### Ethernet

Locking RJ45 EtherCON connector

### Video Output

HDMI 1.4 with lock system



|                    |                             |  |
|--------------------|-----------------------------|--|
|                    | <b>Recommended cable</b>    | UTP CAT6a with EtherCON connectors<br>*Contact Theatrixx Technologies for more information |
| Supported Signals  | <b>Video Format Support</b> | HDMI 1.4   |
|                    | <b>HDCP Support</b>         | HDCP 1.4   |
|                    | <b>Ethernet Support</b>     | 100 Mbps   |
| Physical           | <b>Height</b>               | 50 mm (1.97 in)  |
|                    | <b>Depth</b>                | 180 mm (7.08 in)   |
|                    | <b>Width</b>                | 107 mm (4.21 in)   |
|                    | <b>Weight</b>               | 1 kg (2.2 lbs)   |
| Environmental      | <b>Relative Humidity</b>    | 0 % to 90 % non-condensing   |
| Power Requirements | <b>Power Supply</b>         | Built-in power supply PowerCON True1 input<br>PowerCON True1 output                        |



**Power Consumption**

25W

**Operational Voltage Range**

90-250 V with True1 connectors

**Courtesy Outlet**

Max 10 A, same voltage as input

**In the box**

xVision Receiver HDBT to HDMI (True1)  
HDMI male with locking system to DVI male (1m)  
AC Mains True1 cable (1.5 m, specify plug type at ordering)

---

**Certifications**



DESIGNED & MANUFACTURED  
IN CANADA 

