



HDMI to HDBaseT Transmitter - True1

xVision Converter Series



#XVVHDMI2HDBTT1

Professional equipment in mission-critical applications is all about reliability and confidence. So we started with a clean sheet, and built what might soon become your most trustworthy piece of equipment. Introducing the world's first video converters truly designed for the road. Video converters nowadays are used everywhere on professional A/V events, presentations, live shows and tours and often have a critical role. Yet, they are often the weakest link in the signal chain. Low quality connectors, weak enclosure, external consumer-grade power supply, and overall barebones design that all contribute to a generally unreliable piece of equipment. We wanted to change that, so we designed the xVision Video Converters.

Connections

Video Input

1 x HDMI 1.4 type A with locking system

Ethernet Port

1 x 1 Gbps Ethernet on Neutrik EtherCON

Video Output

1 x HDBaseT 1.0 on shielded EtherCON connector



Supported Signals	Recommended cable	UTP CAT6a with EtherCON connectors *Contact Theatrixx Technologies for more info
	Video Format Support	HDMI 1.4
	HDCP Support	HDCP 1.4
	Ethernet Support	100 Mbps
Physical Specifications	Height	53 mm (2.09 in)
	Depth	180 mm (7.08 in)
	Width	107 mm (4.21 in)
	Weight	1 kg (2.2 lbs)
	Alternate Form Factor	Also available as a Reversible Module
Environnemental Specifications	Relative Humidity	0% to 90% non-condensing



Operating Temperature

0-40 °C

Power Requirements

Power Supply

Built-in power supply
PowerCON True1 input
PowerCON True1 output (loop-thru)

Power Consumption

15W

Voltage Range

100-240V, 50-60Hz
(100-120V, 50-60Hz available with PowerCON/
Edison Nema 5-15)

Courtesy Outlet

Max 10A, same voltage as input

In the Box

xVision Converter HDMI to HDBaseT True1

AC Mains PowerCON True1 cable (1.5m, specify plug
type at ordering)

Certifications



DESIGNED & MANUFACTURED
IN CANADA

