



HDMI to SDI

xVision Converter Series



#XVVHDMI2SDI

Professional equipment in mission-critical applications is all about reliability and confidence. So we started with a clean sheet, and built what might soon become your most trustworthy piece of equipment. Introducing the world's first video converters truly designed for the road. Video converters nowadays are used everywhere on professional A/V events, presentations, live shows and tours and often have a critical role. Yet, they are often the weakest link in the signal chain. Low quality connectors, weak enclosure, external consumer-grade power supply, and overall barebones design that all contribute to a generally unreliable piece of equipment. We wanted to change that, so we designed the xVision Video Converters.

Connections

Video Input

HDMI 1.2 type A with lock system

Video Output

2 x 3G/HD/SD SDI BNC

Supported Signals

3G Format Support

1080p50, 1080p59.94, 1080p60.



HD Format Support

720p50, 720p59.94, 720p60, 1080i50, 1080i59.94, 1080i60, 1080p23.98, 1080PsF23.98, 1080p24, 1080PsF24, 1080p25, 1080PsF25, 1080p29.97, 1080PsF29.97, 1080p30, 1080PsF30

SD Format Support

525/23.98 NTSC, 525/29.97 NTSC.625/25 PAL

SDI Video Sampling

4:2:2 and 4:4:4

SDI Audio Sampling

Sample rate of 48 kHz and 24 bit

SDI Color Space

YUV and RGB

SDI Auto Switching

Automatically detects incoming signal format

SMPTE Standards

425 M Level A & B, 424 M Level A, 292 M, 259 M

Physical

Height

50 mm (1.97 in)

Depth

180 mm (7.08 in)

Width

107 mm (4.21 in)



	Weight	1 kg (2.2 lbs)
Environmental	Relative Humidity	0 % to 90 % non-condensing
Power Requirements	Power Supply	Built-in power supply PowerCON input Edison Nema 5-15 output
	Power Consumption	15W
	Operational Voltage Range	100-120 V 50-60 Hz 100-240V also available (with PowerCON True1)
	Courtesy Outlet	Max 10A, same voltage as input
In the box		xVision converter HDMI to SDI Locking HDMI male to DVI male (1 m) Edison to PowerCON (1.5 m)

Certifications



DESIGNED & MANUFACTURED
IN CANADA 

